



The model VIS-8007 is a 2- Channel 315 RF receiver supplied with antenna. This receiver is designed for use with the VISIONIS VIS-8008 2 channel remote. The receiver operates for opening doors, garage doors, and gates. Very easy and convenient as well for home/store anti-theft security systems. The receiver programs each specific code; no unauthorized person can gain access to the system by reprogramming or duplicating the Transmitter (remote). This transmitter (remote) can be programmed locally into the memory of the receiver.

Model No.	VIS-8007
Operating Frequency	315MHz
Number of Codes	1,048,576
Data Format	PWM
Operating Voltage	DC12V
Receiver Output	C dry contact (NO/NC/COM)
Operating Distance	Up to 160ft (50m) - The maximum range needs to be used in an open area. The distance will start to diminish based on some type of interference such as metal, concrete and others.
Operating Temperature	0°C-70°C or 32°F - 158°F
Current Draw	19mA
Compatible Transmitter	VIS-8008
RF Channels	Two
Remotes	Up to 50 remotes are able to connect to one Receiver
Receiver Output Functions	4 (Default) 4 second momentary, latch, toggle (On/Off), press on function
Connectors	5 screw Terminal (NO, COM, NC + -)(short wire included for each terminal used to facilitate install.)
Case Construction	ABS Plastic
Dimensions	62*43.5*30mm (2.44* 1.71*1.18 Inches)
Weight	43g or 1.52 Ounces
Certifications	FCC
Antenna	Wire lead
Mounting Screws	Comes with two mounting screws



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this kit. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



sales@visionistech.com



www.visionistech.com

Model No.	VIS-8007
Warranty	3 Years
Wire Harness	Included
Power supply	Not included (only included in the form of kits.)



VIS-8007 Board



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this kit. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



sales@visionistech.com



www.visionistech.com