



The VIS-GB106 is a zinc alloy mortise box that is designed for our line of exit buttons but can also be used for other applications and other exit buttons that are not from the brand Visionis. You can use devices that fit this back box with the current measurements: 114Lx70Wx25H (mm) – 4.49Lx2.75Wx0.98H (in.). You may use the following Visionis exit buttons with this box: VIS-7000, VIS-7001, VIS-7002, VIS-7003, VIS-7004, VIS-7007, VIS-7011, VIS-7013.



Model No.	VIS-GB106
Dimensions	114Lx70Wx25H (mm) - 4.49Lx2.75Wx0.98L (in.)
Standard Instruction	Zinc alloy material and surface is coated with chrome
Weight	0.2kg (0.44 pounds)



Disclaimer: VISIONIS reserve the right to go ahead with any modifications of models or features or price without forewarning. All the information and specifications stated in this document are current at the time of publication. Attention: We are not responsible for the improper installation of this kit. If you are not handy with electrical equipment you should contact a professional electrician. You will also need to check with your local Fire authority to see if you need anything else to comply with local Fire Codes. We are not responsible for any damage or fees that can occur.



sales@visionistech.com



www.visionistech.com